

# Powerware® 5125

*Power protection for networked office servers*



**Technology:** Series 5 (line interactive)  
**Rating:** 1000-2200 VA  
**Voltage:** 200-240 Vac  
**Backup time:** Typical 5 min (extendable to several hours)  
**Model:** Cabinet

Designed to ensure clean power and reliable operation of all kinds of IT devices in the network system, Powerware 5125 protects your equipment against five of the nine most common power problems that can harm your equipment or result in corrupted data.

The PW5125 offers the features needed for cost effective networks protection and comes with the proven reliability users have come to expect from Powerware products. In addition to a reliable shut-down solution, Powerware 5125 offers extended runtime capability as well as enhanced connectivity options to manage and monitor the UPS remotely.

#### **Typical Applications:**

- Small networks
- Servers
- Network devices

#### **Product highlights:**

- Extended backup time
- Connectivity options
- Software suite bundled
- ABM™, prolongs battery life by 50%
- Load segments allow scheduled shutdown of non-critical loads
- Multiple Australian outlets for ease of connection

#### **Options:**

- WEB/SNMP card with in-built switching hub
- External battery cabinets
- USB card
- Relay card



**POWERWARE 5125 specifications table**

Rating	1000VA	1500VA	2200VA		
Part number	51251000A	51251500A	51252200A		
Capacity (VA/watts)	1000/700	1500/1050	2200/1600		
Dimensions WxDxH (mm)	162x401x250	162x467x250	205x493x250		
Weight (kg)	16	23	31		
Input connection	IEC320/10A	IEC320/10A	IEC320/16A		
Output connection	4 x AUST. 10A	4 x AUST. 10A	6 x AUST. 10A		
Typical runtime (Full load)	5 min	6 min	5 min		
<b>Operational</b>					
Nominal input voltage (Vac)	220/230/240 Vac				
Input voltage range	166-276 VAC (+20/-30% of nominal)				
Operating frequency	50/60 Hz auto sensing				
Input power factor	Same as load				
Nominal output voltage	220/230/240 Vac				
Output voltage regulation	-10%/+6% of selected nominal voltage				
Overload capacity	110% 3 min; 150% 10 cycles				
Efficiency	95%				
<b>User interface</b>					
LED Informative	LED display				
Standard communication ports	RS232				
Optional	SNMP/WEB card, USB card, relay cards				
<b>Environmental</b>					
Operating temperature	0°C – +40°C				
Storage temperature	-15°C – +55°C				
Altitude	< 3000 m				
Audible noise at 1 metre	< 45dB normal mode < 50dB battery mode				
<b>Certification</b>					
Markings	CE/GS/UL/C-Tick				
Safety	EN 50091-1-1 & UL 1778				
EMC	EN 50091-2, EN6100-3-2				
<b>Battery Runtimes (in minutes full load/half load)*</b>					
Model	Standard Internal Batteries	1 EBM	2 EBMs	3 EBMs	4 EBMs
1000VA	5/14	25/60	55/170	83/199	109/228
1500VA	6/17	33/79	63/146	92/174	120/201
2200VA	5/14	26/60	55/170	81/198	106/224
* Up to 4 EBMs can be connected. EBM runtimes include internal batteries. Run time chart provides typical information. Battery runtimes are approximate and may vary with equipment, configuration, battery age, temperature, etc.					

Invensys Energy Systems Pty Ltd 119-127 Wicks Road North Ryde NSW 2113  
 Tel. +61 2 9878 5000, Fax +61 2 9887 2186  
 ABN 82 054 056 709  
 National Service and Repair Centre: 1300 303 059  
 Sales Offices: Adelaide +61 8 8347 3622 Brisbane +61 7 3891 1205  
 Melbourne +61 3 9797 9097 Perth +61 8 9240 2412  
 Auckland +64 9 576 6842

E-mail: [info.sales@energy.invensys.com](mailto:info.sales@energy.invensys.com)  
 Website: [www.powerware.com.au](http://www.powerware.com.au)

